

Creative Computing II
Finite Impulse Response filters
9th March 2010

This lab sheet introduces the *Octave* `fir1` function for filter design, and covers how to use the filters it produces.

1. This part covers the interface of the `fir1` operator, and how to visualize the filter it produces.
 - (a) construct the 100th-order low-pass FIR filter with a cut-off of 475Hz for a sample rate of 44.1kHz; plot the resulting filter's characteristics using `freqz`.
 - (b) construct the 100th-order high-pass FIR filter with a cut-off of 425Hz for a sample rate of 44.1kHz; plot the resulting filter's characteristics using `freqz`.
 - (c) convolve the two filters' (from parts 1a and 1b) responses together; plot the resulting filter's characteristics using `freqz`.
 - (d) construct the appropriate-order band-pass FIR filter, with the pass-band being 425Hz-475Hz for a sample rate of 44.1kHz. What are the differences between this filter and the one in part 1c?

2. This part covers the use of the filters you have produced in part 1.
 - (a) Read in the sound data from the `scale.wav` file used in lab 13.
 - (b) Using the `filter` function, apply the four filters produced in part 1 to the sound data, and play the resulting filtered sounds using `sound`. Check that you understand the effects of the filters, in the light of your investigations about the frequencies present in the audio file at different times. If you don't understand the effects, check that your filters are correct.
 - (c) Verify that you get the same results using `conv` to apply the filters to the sound data.
 - (d) Perform the same filtering operation using `fft` and its inverse. Can you explain any discrepancy between the results using this method and the previous two?

3. This part applies a filter you have produced to a synthetic tone, in a similar way to the method of operation of Moog synthesizers.
 - (a) Construct a frequency spectrum of 44100 elements, with ones in the 56th bin and every 55 thereafter up to the Nyquist frequency, and the high half of the spectrum being the reverse of the low half.
 - (b) Construct the time-domain signal corresponding to the spectrum in part 3a.
 - (c) Apply the band-pass filter you constructed in part 1d to this signal, and listen to the result.
 - (d) Apply the 1000th-order FIR filter with the same parameters, and listen to the results. Describe the differences in the sound as best you can.